

CAUTION!

- Never set an amplifier on anything that will tip over or collapse under its weight.
- These amplifiers are capable of producing sound pressure levels that may cause hearing loss.
- There are no user serviceable parts inside these units. Always consult a qualified repair facility for service.

WARNING!

- The use and operation of this device constitutes an agreement of full release of any and all liability connected with its use. Only persons familiar with the operation of audio equipment should attempt to operate this device.
- In addition, by use of this device, the user agrees to hold Genz Benz Enclosures, Inc. and its designers, sales agents and all other affiliates and related parties harmless in the event of any accident, injury, damage or loss resulting from such use.
- Manufacturer's sole responsibility is to provide a warranty on the specified performance of the product under normal operating conditions for a period of 1 years.

TranZamp

model **B40**

B A S S A M P L I F I E R



OWNER'S MANUAL

Thank you for choosing TranZamp. These bass amp are is designed with professional features and tone and are ideal for beginners, students or intimate performance settings.

The B40 utilizes the same preamp circuitry but is a more powerful 40 watts with a heavy-duty 10" loudspeaker.

Along with their impressive tone and features, the B40 offers rugged construction and attractive styling to insure years of solid performance and value.

GENZ·BENZ

A Kaman Music Company, Bloomfield, CT
7811 E. Pierce Street, Scottsdale, AZ 85257
PH: 480-941-0705 FAX: 480-946-2412
www.genzbenz.com

GENZ·BENZ

FEATURES



INPUT — Standard 1/4" input designed to provide the best response form all instrument pick-ups.

ACTIVE/PASSIVE SWITCH — This switch sets the input sensitivity for either passive or active (battery powered) basses. The active position reduces the input sensitivity by approx. – 10db.

GAIN CONTROL — This continuously variable control adjusts the input signal to the preamp.

CONTOUR CONTROL — This shape circuit provides a variable "contour" control that provides a wide bandwidth mid-scoop filter in the signal path. With the control in the counter-clockwise position, the filter is effectively removed from the signal path.

ACTIVE EQUALIZATION — The B40 offers an active 3-band EQ network. Each filter provides a cut or boost of 15 db. These low, mid and high frequencies provide a wide range of tone shaping possibilities.

MASTER VOLUME — The master volume control adjusts the overall volume of the amplifier. It is best to operate this control in the 12 o'clock to 3 o'clock position and then adjust the input gain accordingly.

CD/TAPE INPUT — This line level input allows the use of a CD or tape player for practice sessions.

LINE OUT — A line level output is provided for sending a signal from the preamp section to a mixing console for live performance or recording purposes.

HEADPHONE OUTPUT — Use this jack to connect standard headphones (8-600 ohms). When headphones are inserted, the internal speaker is disconnected. (Always protect your ears against excessive volume).

POWER SWITCH — The switch provides power to the unit. The green LED will illuminate when the amp is turned on.

B40 SPECIFICATIONS

Power rating: 40 watts, 4 ohms

Speaker size: 10" loudspeaker

Dimensions: 19"H x17.5"W x 11"D

Weight: 33 lbs.