

*Heartfield*

## ELAN II (31-4100)

035309	TUNING KEY, LEFT, CHROME
035310	TUNING KEY, RIGHT, CHROME
264606	SCREW, TUNING KEY, MTG.
035235	NUT
035183	TRUSS ROD COVER, BLK.
035019	SCREW, TRUSS ROD COVER. BLK.
035137	PICKUP, FRONT
035138	PICKUP, REAR
264751	SCREW, P/U MTG.
264805	SPRING,P/U, 0.5
264802	P/U MTG. RING, BLK.
035017	SCREW, P/U MTG. RING, BLK
264342	CONTROL 1M/250K C
264328	CONTROL 500KG
037260	SWITCH, 5-WAY
264799	RESISTOR 4.7M, 1/4W
264796	RESISTOR 82K, 1/4W
264270	CAPACITOR, .022 50V
035131	KNOB, CONTROL BLK.
035132	KNOB, 5-WAY SWITCH, BLK.
035024	JACK
035260	RUBBER WASHER, JACK
035170	STRAP BUTTON
264265	SCREW, STRAP BUTTON
035277	FELT WASHER, WHITE
264634	BACK PLATE, TR, WHT.
035232	BACK PLATE, CONTROL, WHT.
264643	SCREW, BACK PLATE, BLK.
035025	PIPE WRENCH, TRUSS ROD
035026	HEX WRENCH
037251	BRIDGE ASSY
017031	SCREW, STRING LENGTH
019394	SPRING, LONG, BLK.
019395	SPRING, SHORT, BLK.
019656	SCREW, PLATE, MTG.
026099	BRIDGE SECTION
026779	SCREW, ALLEN, 1 & 6TH
026780	SCREW, ALLEN, CTR.
036527	BRIDGE PLATE
036530	BRIDGE BLOCK
036531	SPRING CLIP, TR. ARM
036614	BUSHING NYLON, BLK.
036615	SCREW SET, TR. ARM

MODEL EL(ELAN')-I,II

31-4000  
31-4100

SELECTOR SWITCH  
00372-600

RESISTOR 82k $\Omega$   
264796

RESISTOR 4.7M $\Omega$   
264799

CAPACITOR MYL, 223  
264270

TBX (DUAL POT)  
TONE CONTROL  
1M $\Omega$ A / 250k $\Omega$ A  
264342

SIDE JACK  
035024

VOLUME  
500k $\Omega$  G  
264760

TO BRIGE PIECE

(FRONT)  
035137

(REAR)  
035138

PICK-UP

A  
B

C  
D

1 AxB  
2 A+D  
3 AxB+CxD  
4 B+C  
5 CxD

DRAW



91-2-18

**Heartfield**